



# DEFENDER

Unlike any other UPS!



**Power Center 1000**  
Line Interactive

*Power Center*

Microprocessor control guarantees high reliability.

Equipped with Boost and Buck AVR to stabilize input voltage.

Built-in DC start function enables UPS to be started up without AC power supplied.

Smart RS-232 Communication Port with Software.

Green Power Function for energy saving.

Auto restart while AC recovery.

Provides Modem/Phone line surge protection.

Provides Overload Protection.

comprehensive  
warranty  
**2**  
Year

**PLUS**  
Guarantee  
Consented Equipment Protection  
VANCE.COM

v-care  
Backed 24x7

**VENCE**  
Power to Perfection

# Power Center<sup>®</sup>

SPECIFICATIONS		
<b>MODEL</b>		<b>Power Center 1000</b>
<b>CAPACITY</b>	VA	1000VA
<b>INPUT</b>	Voltage	230VAC
	Voltage Range	158-280VAC
<b>OUTPUT</b>	Voltage	230VAC
	Voltage Regulation(Batt.Modde)	±10%
	Frequency	50Hz or 60Hz
	Frequency Regulation(Batt.Modde)	±1Hz
	Output Waveform	Modified Sine-wave
<b>BATTERY</b>	Battery Type & Number	12V/9Ah x 1pc
	Typical load	20 minutes
	Recharge Time	8 hours to 90% after complete discharge
<b>TRANSFER TIME</b>	Typical	2-6ms
<b>INDICATOR</b>	AC Mode	Green Lighting I
	Battery Mode	Green Flashing
<b>AUDIBLE ALARM</b>	Battery Mode	Alarm every 10 seconds
	Low Battery	Alarm every second
	Overload	Alarm every 0.5 second
	Battery Replacement	Alarm every 2 seconds
	Fault	Continuously Alarm
<b>PROTECTION</b>	Full Protection	Discharge, Overcharge and Overload protection
<b>PHYSICAL</b>	Dimension (DxWxH) mm	330 x 100 x 140
	Net Weight (kgs)	6.5
<b>ENVIRONMENT</b>	Operating Environment	0-40°C, 0-90% Relative Humidity (non-condensing)
	Noise Level	Less than 40dB
<b>INTERFACE</b>	Smart RS-232	Support Windows 95/98/NT/2000/XP, Novell and Linux
<b>OUTPUT CONNECTORS</b>	Backup Only	IEC320 X 3 Telephone Line Protector



Manufactured by : Datron Products Co., Ltd. P.O. Box 25-32, Taipei, Taiwan., On OEM basis for VENCE.

Vence (Pte) Limited. No. 22, Dudley Senanayake Mw. (Castle St), Colombo 08, Sri Lanka. Phone: +94(0)11-4-610-101 Fax: +94(0)11-2-690-970 E-mail: info@vence.lk Website: www.vence.lk